

wallbox

Smart charging for home



We're Wallbox. We innovate to make things simpler.

- ✓ **Easy**
Exceptional chargers that are easy to use.
- ✓ **Fast**
Faster charging than with a conventional plug.
- ✓ **Smart**
Manage how fast and when you want to charge.
- ✓ **Compatible**
Compatible with all domestic installations as well as plug-in electric and hybrids.
- ✓ **Connected**
Monitor the status of your charger and control it remotely from anywhere.
- ✓ **Experienced**
Our team of expert technicians makes sure you get the service you need.




Boost your Home, Charge Smart

Power Boost

Power Boost balances the available energy dynamically among the charger and the rest of the devices in the house. This helps you to avoid exceeding your infrastructure's available power and prevents blackouts.

- ✓ **INTELLIGENT CHARGING:**
Measures how much electricity your house consumes and uses the rest for your car.
- ✓ **CHARGE SAFELY:**
Protect your building's electric installations and the local grid.
- ✓ **OPTIMIZE USAGE:**
Always charges at maximum power available.



**Power Boost is an additional feature to your charger. Compatible with Pulsar Plus, Commander 2 and Quasar.*

Contact: sales@wallbox.com
www.wallbox.com

PULSAR PLUS

Our bestselling charger



Connected
Control your Pulsar with your smartphone via Bluetooth or WiFi.



Easy
LED Lighting system indicates charging status.



Smart
Add load balancing with Power Boost to allow faster charging when more power is available.

GENERAL SPECIFICATIONS	
Charger:	AC
Connector:	Type 1 or Type 2 (7.4 kW) / Type 2 (11 kW and 22 kW)
Charging mode:	Mode 3
Dimensions:	166x163x82 mm (without cable)
Weight:	1 kg (without cable)
Cable length:	5 m (7 m optional)

ELECTRICAL SPECIFICATIONS	
Maximum Power:	7.4 kW (3 Phase) / 22 kW (3 Phase)
Maximum current:	7.4 kW 32 A (3P) / 11 kW 16 A (3P) / 22 kW 32 A (3P)
Adjustable current:	from 6 A to 32 A
DC leakage protection:	Yes

USER INTERFACE	
Charge status:	Halo RGB LED / myWallbox App / myWallbox Portal
User Interface:	myWallbox App / myWallbox Portal
User Identification:	myWallbox App

CONNECTIVITY	
Connection:	Bluetooth / Wi-Fi

COMMANDER 2

Advanced home charging



Easy-to-use
7-inch touchscreen for a personalized and secure user interface.



Controlled charging
Create multiple user-profiles and schedule charges when tariffs are lower.



Connected
Insights on every charging session via Bluetooth and WiFi connection to MyWallbox app and portal.

GENERAL SPECIFICATIONS	
Charger:	AC
Connector:	Type 1 or Type 2 (7.4 kW) / Type 2 (11 kW and 22 kW)
Charging mode:	Mode 3
Dimensions:	221x152x115 mm (without cable)
Weight:	2.4 kg (without cable)
Cable length:	5m (7m optional)

ELECTRICAL SPECIFICATIONS	
Maximum Power:	7.4 kW (1 Phase) / 22 kW (3 Phase)
Maximum current:	7.4 kW 32 A (1P) / 11 kW 16 A (3P) / 22 kW 32 A (3P)
Adjustable current:	from 6 A to 32 A
DC leakage protection:	Yes

USER INTERFACE	
Charge status:	RGB LED / Screen information / myWallbox App and Portal
User Interface:	7" Touchscreen / myWallbox App / myWallbox Portal
User Identification:	Pin code / RFID / myWallbox App

CONNECTIVITY	
Connection:	Bluetooth / Wi-Fi / Ethernet / 4G (Optional)

QUASAR

The first bidirectional charger for home



Innovative
The lightest and smallest DC charger of its kind



Cutting-edge technology
Advanced facial recognition and gesture control



Bidirectional
Allows you to charge and discharge your vehicle, feeding energy from your car back to the grid (V2G) or to your home (V2H).

GENERAL SPECIFICATIONS	
Charger:	DC
Connector:	CCS or CHADEMO
Charging mode:	Mode 4
Dimensions:	350x350x150 mm (without cable)
Weight:	22 kg (without cable)
Cable length:	5 m (7 m optional)

ELECTRICAL SPECIFICATIONS	
Maximum Power:	7.4 kW (Depends on country-specific regulations)
Maximum current:	7.4 kW 32 A
Adjustable current:	from 6 A to 32 A
DC leakage protection:	Yes

USER INTERFACE	
Charge status:	Color Screen / RGB LED
User Interface:	myWallbox App / Portal / Gesture control (Optional)
User Identification:	myWallbox App / RFID (Optional) / Facial recognition (Optional)

CONNECTIVITY	
Connection:	Bluetooth / Wi-Fi / Ethernet / 5G/4G (Optional)

